

RAZDELITEV PREDNOSTNIH FREKVENČ
ZA SISTEME FWA IN P-P NA FREKVENČNEM OBMOČJU 28 GHz

KANALI 28 MHz					PODROČJE															
Kanal št.	Osrednja frekvenca		SVK/ POL	CZE/ SVK/ POL	CZE/ POL	AUT/ CZE	CZE/ SVK	AUT/ CZE/ SVK	AUT/ SVK	AUT/ HNG/ SVK	AUT/ HNG	HNG/ SVK	HNG/ SVN SVN	AUT/ HNG/ SVN SVN	AUT/ SVN SVN	SVK/ POL/ UKR	SVK/ UKR	HNG/ SVK/ UKR	HNG/ UKR	POL/ UKR
	Nižji pas	Višji pas																		
19	28066,5	29074,5	SVK/	C	CZE	AUT	SVK	C	SVK	C	AUT	SVK	HNG	C	AUT	C	SVK	C	HNG	UKR
20	28094,5	29102,5	POL	C	POL	AUT	CZE	C	AUT	C	AUT	HNG	SVN	C	AUT	C	UKR	C	UKR	POL
21	28122,5	29130,5	SVK/	SVK	CZE	CZE	SVK	SVK	SVK	SVK	HNG	SVK	SVN	SVN	SVN	SVK	SVK	SVK	HNG	POL
22	28150,5	29158,5	SVK/	CZE	CZE	CZE	CZE	CZE	SVK	HNG	HNG	HNG	HNG	HNG	SVN SVN	UKR	UKR	HNG	HNG	UKR
23	28178,5	29186,5	POL	POL	POL	AUT	CZE	AUT	AUT	AUT	AUT	HNG	SVN	AUT	AUT	POL	UKR	UKR	UKR	POL
24	28206,5	29214,5	SVK/	SVK	POL	AUT	SVK	SVK	SVK	SVK	AUT	SVK	SVN	SVN	SVN	SVK	SVK	SVK	HNG	POL
25	28234,5	29242,5	POL	CZE	CZE	CZE	CZE	CZE	AUT	HNG	HNG	HNG	HNG	HNG	SVN	UKR	UKR	UKR	UKR	UKR
26	28262,5	29270,5	POL	POL	POL	AUT	SVK	AUT	AUT	AUT	AUT	HNG	HNG	AUT	AUT	POL	SVK	HNG	HNG	POL
27	28290,5	29298,5	SVK/	SVK	CZE	CZE	SVK	SVK	SVK	SVK	HNG	SVK	SVN	SVN	SVN	SVK	SVK	SVK	UKR	UKR
28	28318,5	29326,5	POL	CZE	CZE	CZE	CZE	CZE	SVK	HNG	HNG	HNG	HNG	HNG	SVN	UKR	UKR	HNG	HNG	UKR
29	28346,5	29354,5	POL	POL	POL	AUT	CZE	AUT	AUT	AUT	AUT	SVK	SVN	AUT	AUT	POL	UKR	UKR	UKR	POL
30	28347,5	29382,5	SVK/	SVK	POL	CZE	SVK	SVK	SVK	SVK	HNG	SVK	SVN	SVN	SVN	SVK	UKR	UKR	UKR	UKR
31	28402,5	29410,5	SVK/	CZE	CZE	CZE	CZE	CZE	AUT	HNG	HNG	HNG	HNG	HNG	AUT	UKR	SVK	HNG	HNG	UKR
32	28430,5	29438,5	POL	POL	POL	AUT	SVK	AUT	AUT	AUT	AUT	SVK	HNG	AUT	AUT	POL	SVK	SVK	UKR	POL